



### Product Overview

The **DualDimmer K020** has two 0-10V controls for use with tunable white LED lighting products such as the LUXdrive K021 DynamicWhiteStrip as well as LED products with a single 0-10V input such as the 7011 ElaraStrip II, A006 LuxStrip II, I033 DuoStrip, A009 BuckBlock, A011 FlexBlock, 3021/3023 BuckPuck LED drivers, and others compatible with a 0-10V current sinking control. Features logarithmic response and reverse polarity protection.



**WARNING:** Miswiring Low Voltage Dimming Control could cause permanent damage to dimmer.

**Do Not** connect this control to line voltage.

**Do Not** connect with power applied.

Maximum recommended operating current is 25mA per channel.



### Contents

- K020 DualDimmer with mounting plate
- Installation Hardware, mounting screws, and wire nuts

### Ordering Information

Product ID	Color Options
<u>K020</u>	<u>White</u>

Example: K020-W

### Wiring Diagrams

